

# AMMETER AMM9043



## SPECIFICATION

Type	: ICD Ammeter with LED Display
Current Input	: 1A / 5A
Working Current Range	: 2 to 120% of rated current
Display	: 3½ Digit 0.5" seven segment Red LED
Accuracy	: ±1% Over full scale
Resolution	: 1A for range upto 1000A 0.01KA for range above 1000A
CT Ratio	: Field Selectable
LED Indications	: 3 Phase Currents
Current Display Selection	: By Push button on the front panel
Burden on Current input	: 0.25 VA per phase
Auxiliary Power Supply	: External 110/240V AC RMS
Burden on Auxiliary Supply:	3 VA
Operating Temperature	: 55° C Max.
Box Dimension	: 96(H) x 96(W) x 80(D) mm OR 48(H) x 96(W) x 120(D) mm
Mounting	: Panel
Enclosure	: ABS Plastic case

Single Phase Ammeter Model AMM 9041 is also available

## APPLICATIONS

- Panel Metering in Sub Stations
- Power Generation Plants, Genset Panels
- Control Panels
- Test Benches
- Switch Boards
- Power Distribution Panels

PLEASE PROVIDE THE FOLLOWING DETAILS WHILE PLACING YOUR ORDER / ENQUIRY

1. Current Input    2. HT / LT Application    3. PT Primary    4. Self Powered / External Supply.

## OUR RANGE OF PRODUCTS

Volt Meter, Ammeter, VAF Meter, Energy Meter, Dual Source Meter, Load Manager, Power Multimeter, Trivector Meter, Maximum Demand Controller, Harmonic Indicator, Power Factor Controller, Smart PF Controller, Power Factor Correction Panel, AC Voltage Controller, AC Current Controller, Motor Protection System, Voltage/Current/Power/Frequency Transducer, Power Transmitter, Energy Management and Billing Systems etc...